

Model: H100

CE, IEC1010

Wide Range Light Meter



Description:

The model H100 is an ideal meter for measuring light levels in both lux and foot-candle units of measure. The meters wide measuring range allows it to be used in many applications such as interior design, photography, energy audits and installation of electrical fixtures. It is perfect for general applications, including measuring lighting levels in the home, office, restaurant, school, etc.

Features:

- Large LCD display with bar graph
- Wide measurement ranges:
40.00/400.0/4,000/40,000/400,000lux
- Display resolution: 0.04lux to 100lux,
0.01fc to 10fc (foot-candle = fc)
- 4 light type select (Tungsten,
Fluorescent, Sodium or Mercury)
- Sensor meet C.I.E. spectrum, 2 filters
- Data hold, Record (max., min.)
- lux or foot-candle unit selection
- Longer battery life compared to 9V
- Displays values in both lux or foot-candle
- Two year warranty

Applications:

- Science experiments
- Photography
- Manufacturing
- Agriculture
- Artistry